

# FREQ 5 STROBE



Add more creativity to your lightshow with the American DJ FREQ 5 revolutionary 5-Zone LED Strobe. This 2-FX-IN-1 fixture features a traditional LED strobe + 5-Zone chase effect. The Zone chase effect gives lighting designers the ability to display this strobe bar vertical or horizontal creating chasing white light for a dynamic energy-driven light show. The FREQ 5 offers full DMX control with 4 DMX channel modes, dimming, strobe speed and chase speed. Users can also run the FREQ 5 in sound active mode, or manually control strobe speed and dimming on the back of the unit from it's potentiometer knobs. The FREQ 5 uses five 5-Watt bright white LEDs and consumes a maximum of 28-Watts of power.

## Specifications

- Revolutionary 5-Zone LED Chasing Strobe
- 2-FX-IN-1: Traditional LED Strobe + 5-Zone chase effect
- 5x 5-Watt White bright LEDs (30,000 hr. rated)
- 4-Button DMX LED Display
- 3 Operational modes: DMX controller, Master/Slave & Sound Active
- 4 DMX Channel modes (1, 2, 5 or 7 Ch.)
- Strobe speed: control via DMX or manually from the potentiometer knob on rear
- 0-100% dimming: control via DMX or manually from the potentiometer knob on rear
- Includes exciting sound activate built-in programs
- Contrast Effect Movement (Master/Slave mode): LED effect will move in opposite directions
- Strobes 1200 times per minute.
- No Moving Parts
- Fan cooled
- Runs extremely cool! - NO Duty Cycles! – Run all night!
- Includes hanging bracket + safety hook on rear panel
- IEC AC IN/OUT on rear to daisy-chain power (up to 13 units)
- Compatible with American DJ UC3 Series easy-to-use controllers (sold Separately)
- Power Consumption: 28W maximum
- Multi-voltage operation: AC 100-240V 50/60Hz- IEC socket
- Dimensions (LxWxH): 12"x 5.5"x 5.5" / 302x140x140mm
- Weight: 5 lbs. / 2 kg.

*Specifications subject to change without notice.*

