

ADJ MIRAGE Q6 PAK BLACK - DMX TRAITS

CHANNEL											VALUE	FUNCTION
4Ch	6Ch	7Ch	8Ch	9ACh	9BCh	10Ch	11Ch	12Ch	15Ch	18Ch		
1	1	1	1	1	1	1	1	1	1	1	0-255	All Red, 0~100%
			2							2	0-255	All Red Fine 16-bit
2	2	2	3	2	2	2	2	2	2	3	0-255	All Green, 0~100%
			4							4	0-255	All Green Fine 16-bit
3	3	3	5	3	3	3	3	3	3	5	0-255	All Blue, 0~100%
			6							6	0-255	All Blue Fine 16-bit
4	4	4	7	4	4	4	4	4	4	7	0-255	All Amber, 0~100%
			8							8	0-255	All Amber Fine 16-bit
					5		5	5	5	9	0-255	Color Macros, See Color Macros (page 29)
					6	5	6	6	6	10	0-255	Color Temperature 2300-9900K Linear, 0~100%
												Shutter, Strobe
											0-31	LEDs Off
											32-63	LEDs On
											64-95	Strobe effect slow to fast
	5	5		5	7	6	7	7	7	11	96-127	LEDs On
											128-159	Pulse-effect in sequences
											160-191	LEDs On
											192-223	Random strobe effect slow to fast
											224-255	LEDs On
	6	6		6	8	7	8	8	8	12	0-255	Dimmer (Intensity), Intensity 0 to 100%
					9	8	9	9	9		0-255	Dimmer Fine 16-bit
												Auto programs:
											0-10	Off
											11-26	Auto Program 1
											27-43	Auto Program 2
											44-60	Auto Program 3
											61-76	Auto Program 4
											77-93	Auto Program 5
											94-110	Auto Program 6
											111-126	Auto Program 7
											127-143	Auto Program 8
											144-160	Auto Program 9
											161-176	Auto Program 10
											177-193	Auto Program 11
											194-210	Auto Program 12
											211-226	Auto Program 13
											227-255	No Function
				8					11	14	0-255	Auto Programs Speed, Slow to Fast
				9					12	15	0-255	Auto Programs Fade, Less to More
												Dim Mode
											0-20	Standard
											21-40	Stage
											41-60	TV
											61-80	Architectural
											81-100	Theatre
											101-120	Stage 2
											121-140	Dim Speed from Fast to Slow (0.1-10s)
											141-255	Default to Unit Setting

DMX TRAITS

CHANNEL											VALUE	FUNCTION
4Ch	6Ch	7Ch	8Ch	9ACh	9BCh	10Ch	11Ch	12Ch	15Ch	18Ch		
						9	10	11	14	17		Dim Curves
											0-20	Linear
											21-40	Square
											41-60	Inv. Squa
											61-80	S. Curve
											81-255	No Function
						10	11	12	15	18		Refresh Rates
											0-15	Default to Unit Setting
											16-30	900HZ
											31-45	1000HZ
											46-60	1100HZ
											61-75	1200HZ
											76-90	1300HZ
											91-105	1400HZ
											106-120	1500HZ
											121-135	2500HZ
											136-150	4000HZ
											151-165	5000HZ
											166-180	10000HZ
											181-195	15000HZ
											196-210	20000HZ
											211-225	25000HZ
											226-255	No Function