

# PRO 38B LED RC



The ADJ PRO38B RC is high output black Par Can with twelve 1-Watt LEDs that is ideal for lighting up stages, dance floors and entertainment venues. The fixture's RGB color mixing allows users to get a full spectrum of color from one Par Can. The PRO38B RC features an Infrared wireless remote to control what would normally require a DMX controller or adjustments made by hand on the rear panel. Aim the wireless remote at the unit and control features such as: Black Out, built-in programs, flash, DMX addressing and RGB color change.

This fixture uses LEDs rated at 50,000 hours with a maximum power draw of 15W. DMX addressing may also be changed by the unit's 3-button LED display. The PRO64B RC has a dual hanging bracket that makes it easy to set on the floor.

## Specifications:

- Black Ultra bright Par 38 with 12x 1-Watt LEDs (4 Red, 4 Green, & 4 Blue LEDs)
- Great for performance stages where traditional par cans emit a lot of heat onto performers
- Includes wireless infrared remote control up to 30 ft./10M (Model: ADJ LED RC)
- 7 DMX Channel modes: 1, 2, 3, 4, 5, 6 or 7 channel modes
- 6 Operational modes: Manual Color Mode; Color Change Mode; Color Fade Mode; Auto (Program Run) Mode; Sound Active Mode and DMX-512 Mode
- Smooth RGB color mixing (fast or slow color change operation)
- Flicker-free operation for film and television
- 32 built-in Color Macros
- Color strobe effect
- Electronic Dimming: 0 - 100%
- Beam angle: 30-degree
- Linkable via 3-pin XLR cable (In/Out)
- 3-button LED display on rear panel
- Dual bracket system allows fixture to be hung or set on the ground
- Power Draw: 15W max

- ETL & ETL Approved
- Run all night - No duty cycle
- Long Life LEDs (50,000 hrs.)
- Multi-voltage: 90-240V, 50/60Hz
- Dimensions (LxWxH): 7.25" x 7.25" x 9.5" / 185x185x240mm
- Weight: 4 lbs. /1.5 kgs.

## ADJ LED RC Infrared Remote Control Features:

- Black Out: Turns fixture On/Off
- Auto Run: Automatically run through built-in programs
- Program Selection: Access units built-in programs
- Flash: Strobe effect
- Speed: Control speed of Auto Run
- DMX Mode Select
- Sound Active: Activates sound active mode
- Slave: Designates the fixture as a "slave" fixture in the Master Slave configuration
- Set Address: Set DMX Address on a fixture
- RGB Buttons: Adjust RGB colors with the "+" and "-" buttons
- + and - Buttons: Adjust flash rate, speed of the Auto Run and Program Selection

*Specifications subject to change without notice.*

**Lighting the Future.**



Check out video footage of this effect @  
[www.americandj.com](http://www.americandj.com)

[www.americandj.com](http://www.americandj.com) • [www.americandj.eu](http://www.americandj.eu)