

ADJ COB CANNON LP200STX - DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
5 CH	8A CH	8B CH	9 CH	10A CH	10B CH	12 CH	13 CH	16 CH	20 CH		
1	1		1	1	1	1	1	1	1		Red
										0-255	0 - 100%
				2					2		Red Fine
										0-255	Red fine adjustment, 16 bit
2	2		2	3	2	2	2	2	3		Green
										0-255	0 - 100%
				4					4		Green Fine
										0-255	Green fine adjustment, 16 bit
3	3		3	5	3	3	3	3	5		Blue
										0-255	0 - 100%
				6					6		Blue Fine
										0-255	Blue fine adjustment, 16 bit
4	4		4	7	4	4	4	4	7		Amber
										0-255	0 - 100%
				8					8		Amber Fine
										0-255	Amber fine adjustment, 16 bit
5	5		5	9	5	5	5	5	9		Lime
										0-255	0 - 100%
				10					10		Lime Fine
										0-255	Lime fine adjustment, 16 bit
		1			6	6	6	6	11		Color Macros
										0-255	Refer to Color Macros section of this manual
		2	6		7		7	7	12		Color Temperature
										0-255	2300K - 9900K Linear
											Shutter, Strobe
										0-31	LEDs Off
										32-63	LEDs On
										64-95	Strobe effect, slow to fast
										96-127	LEDs On
										128-159	Pulse effect in sequences
										160-191	LEDs On
										192-223	Random strobe effect, slow to fast
										224-255	LEDs On
	7	4	8		9	8	9	9	14		Dimmer Intensity
										0-255	Intensity 0 - 100%
	8	5	9		10	9	10	10			Dimmer Fine
										0-255	Dimmer fine adjustment, 16 bit

ADJ COB CANNON LP200STX - DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION	
5 CH	8A CH	8B CH	9 CH	10A CH	10B CH	12 CH	13 CH	16 CH	20 CH			
						10		11	15		Auto Programs	
										0-10	Off	
										11-26	Program 1	
										27-43	Program 2	
										44-60	Program 3	
										61-76	Program 4	
										77-93	Program 5	
										94-110	Program 6	
										111-126	Program 7	
										127-143	Program 8	
										144-160	Program 9	
										161-176	Program 10	
										177-193	Program 11	
										194-210	Program 12	
										211-226	Program 13	
										227-255	No Function	
						11		12	16		Auto Programs Speed	
										0-255	Slow to fast	
						12		13	17		Auto Programs Fade	
										0-255	Least fade to most fade	
		6						11	14	18		Dim Mode
											0-20	Default to unit setting
											21-40	Standard
											41-60	Stage
											61-80	TV
											81-100	Architectural
											101-120	Theatre
											121-140	Stage 2
												Dim Speed
											141	0.1 sec
											142	0.2 sec
											143	0.3 sec
											144	0.4 sec
											145	0.5 sec
											146	0.6 sec
											147	0.7 sec
											148	0.8 sec
											149	0.9 sec
											150	1.0 sec
											151	1.5 sec
											152	2.0 sec
											153	3.0 sec
											154	4.0 sec

ADJ COB CANNON LP200STX - DMX TRAITS

CHANNEL										DMX VALUES	FUNCTION
5 CH	8A CH	8B CH	9 CH	10A CH	10B CH	12 CH	13 CH	16 CH	20 CH		
		6					11	14	18		Dim Speed (continued)
										155	5.0 sec
										156	6.0 sec
										157	7.0 sec
										158	8.0 sec
										159	9.0 sec
										160	10.0 sec
										161-255	Default to unit setting
		7					12	15	19		Dim Curves
										0-20	Square
										21-40	Linear
										41-60	Inv Squa
										61-80	S Curve
										81-255	No Function
		8					13	16	20		Refresh Rate
										0-15	Default to unit setting
										16-30	900 Hz
										31-45	1000 Hz
										46-60	1100 Hz
										61-75	1200 Hz
										76-90	1300 Hz
										91-105	1400 Hz
										106-120	1500 Hz
										121-135	2500 Hz
										136-150	4000 Hz
										151-165	5000 Hz
										166-180	10000 Hz
										181-195	15000 Hz
										196-210	20000 Hz
										211-225	25000 Hz
										226-255	No Function