

ADJ ELECTRAPIX PAR 7 - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
5Ch	6Ch	9Ch	13Ch	22Ch	24Ch	42Ch	45Ch	60Ch		
	1	1		1	1				000 - 255	<i>All Red</i> , 0 - 100%
	2	2		2	2				000 - 255	<i>All Green</i> , 0 - 100%
	3	3		3	3				000 - 255	<i>All Blue</i> , 0 - 100%
	4	4		4	4				000 - 255	<i>All Amber</i> , 0 - 100%
	5	5		5	5				000 - 255	<i>All Lime</i> , 0 - 100%
	6	6		6	6				000 - 255	<i>All UV</i> , 0 - 100%
						1	1	1	000 - 255	<i>Red 1</i> , 0 - 100%
						2	2	2	000 - 255	<i>Green 1</i> , 0 - 100%
						3	3	3	000 - 255	<i>Blue 1</i> , 0 - 100%
						4	4	4	000 - 255	<i>Amber 1</i> , 0 - 100%
						5	5	5	000 - 255	<i>Lime 1</i> , 0 - 100%
						6	6	6	000 - 255	<i>UV 1</i> , 0 - 100%
						7	7	7	000 - 255	<i>Red 2</i> , 0 - 100%
						8	8	8	000 - 255	<i>Green 2</i> , 0 - 100%
						9	9	9	000 - 255	<i>Blue 2</i> , 0 - 100%
						10	10	10	000 - 255	<i>Amber 2</i> , 0 - 100%
						11	11	11	000 - 255	<i>Lime 2</i> , 0 - 100%
						12	12	12	000 - 255	<i>UV 2</i> , 0 - 100%
						13	13	13	000 - 255	<i>Red 3</i> , 0 - 100%
						14	14	14	000 - 255	<i>Green 3</i> , 0 - 100%
						15	15	15	000 - 255	<i>Blue 3</i> , 0 - 100%
						16	16	16	000 - 255	<i>Amber 3</i> , 0 - 100%
						17	17	17	000 - 255	<i>Lime 3</i> , 0 - 100%
						18	18	18	000 - 255	<i>UV 3</i> , 0 - 100%
						19	19	19	000 - 255	<i>Red 4</i> , 0 - 100%
						20	20	20	000 - 255	<i>Green 4</i> , 0 - 100%
						21	21	21	000 - 255	<i>Blue 4</i> , 0 - 100%
						22	22	22	000 - 255	<i>Amber 4</i> , 0 - 100%
						23	23	23	000 - 255	<i>Lime 4</i> , 0 - 100%
						24	24	24	000 - 255	<i>UV 4</i> , 0 - 100%
						25	25	25	000 - 255	<i>Red 5</i> , 0 - 100%
						26	26	26	000 - 255	<i>Green 5</i> , 0 - 100%
						27	27	27	000 - 255	<i>Blue 5</i> , 0 - 100%
						28	28	28	000 - 255	<i>Amber 5</i> , 0 - 100%
						29	29	29	000 - 255	<i>Lime 5</i> , 0 - 100%
						30	30	30	000 - 255	<i>UV 5</i> , 0 - 100%
						31	31	31	000 - 255	<i>Red 6</i> , 0 - 100%
						32	32	32	000 - 255	<i>Green 6</i> , 0 - 100%
						33	33	33	000 - 255	<i>Blue 6</i> , 0 - 100%
						34	34	34	000 - 255	<i>Amber 6</i> , 0 - 100%
						35	35	35	000 - 255	<i>Lime 6</i> , 0 - 100%

ADJ ELECTRAPIX PAR 7 - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
5Ch	6Ch	9Ch	13Ch	22Ch	24Ch	42Ch	45Ch	60Ch		
						36	36	36	000 - 255	UV 6 , 0 - 100%
						37	37	37	000 - 255	Red 7 , 0 - 100%
						38	38	38	000 - 255	Green 7 , 0 - 100%
						39	39	39	000 - 255	Blue 7 , 0 - 100%
						40	40	40	000 - 255	Amber 7 , 0 - 100%
						41	41	41	000 - 255	Lime 7 , 0 - 100%
						42	42	42	000 - 255	UV 7 , 0 - 100%
			1	7	7			43	000 - 255	RGBAL+UV Color Macros , see Color Macros section
		7		8	8		43	44	000 - 255	Background Red , 0 - 100%
		8		9	9		44	45	000 - 255	Background Green , 0 - 100%
		9		10	10		45	46	000 - 255	Background Blue , 0 - 100%
			2	11	11			47	000 - 255	RGB Background Color Macros , see Color Macros section
1			3	12	12			48	000 - 255	Color Temperature , 2300 - 9900K Linear
2			4	13	13			49		White Color Temperature Presets
									000 - 022	Open
									023	2300K
									024	2400K
									025	2500K
									026	2600K
									027	2700K
									028	2800K
									029	2900K
									030	3000K
									031	3100K
									032	3200K
									033	3300K
									034	3400K
									035	3500K
									036	3600K
									037	3700K
									038	3800K
									039	3900K
									040	4000K
									041	4100K
									042	4200K
									043	4300K
									044	4400K
									045	4500K
									046	4600K

ADJ ELECTRAPIX PAR 7 - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
5Ch	6Ch	9Ch	13Ch	22Ch	24Ch	42Ch	45Ch	60Ch		
2			4	13	13			49		White Color Temperature Presets (continued)
									047	4700K
									048	4800K
									049	4900K
									050	5000K
									051	5100K
									052	5200K
									053	5300K
									054	5400K
									055	5500K
									056	5600K
									057	5700K
									058	5800K
									059	5900K
									060	6000K
									061	6100K
									062	6200K
									063	6300K
									064	6400K
									065	6500K
									066	6600K
									067	6700K
									068	6800K
									069	6900K
									070	7000K
									071	7100K
									072	7200K
									073	7300K
									074	7400K
									075	7500K
									076	7600K
									077	7700K
									078	7800K
									079	7900K
									080	8000K
									081	8100K
									082	8200K
									083	8300K
									084	8400K
									085	8500K

ADJ ELECTRAPIX PAR 7 - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
5Ch	6Ch	9Ch	13Ch	22Ch	24Ch	42Ch	45Ch	60Ch		
2			4	13	13			49		<i>White Color Temperature Presets (continued)</i>
									086	8600K
									087	8700K
									088	8800K
									089	8900K
									090	9000K
									091	9100K
									092	9200K
									093	9300K
									094	9400K
									095	9500K
									096	9600K
									097	9700K
									098	9800K
									099	9900K
									100 - 255	No Function
3			5	14	14			50		<i>Shutter, Strobe</i>
									000 - 031	LEDs Off
									032 - 063	LEDs On
									064 - 095	Strobe Effect, slow to fast
									096 - 127	LEDs On
									128 - 159	Pulse Effect in Sequences
									160 - 191	LEDs On
									192 - 223	Random Strobe Effect, slow to fast
									224 - 255	LEDs On
4			6	15	15			51	000 - 255	<i>Dimmer Intensity, 0 - 100%</i>
5			7	16	16			52	000 - 255	<i>Dimmer Fine Intensity</i>

ADJ ELECTRAPIX PAR 7 - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
5Ch	6Ch	9Ch	13Ch	22Ch	24Ch	42Ch	45Ch	60Ch		
										<i>RGBAL+UV Programs</i>
									000 - 010	Off
									011 - 026	Auto Program 1
									027 - 043	Auto Program 2
									044 - 060	Auto Program 3
									061 - 076	Auto Program 4
									077 - 093	Auto Program 5
			8	17	17			53	094 - 110	Auto Program 6
									111 - 126	Auto Program 7
									127 - 143	Auto Program 8
									144 - 160	Auto Program 9
									161 - 176	Auto Program 10
									177 - 193	Auto Program 11
									194 - 210	Auto Program 12
									211 - 226	Auto Program 13
									227 - 255	No Function
			9	18	18			54	000 - 255	<i>RGBAL+UV Programs Speed</i> , slow to fast
			10	19	19			55	000 - 255	<i>RGBAL+UV Programs Fade</i> , least to most
										<i>RGB Background Programs</i>
									000 - 010	Off
									011 - 026	Auto Program 1
									027 - 043	Auto Program 2
									044 - 060	Auto Program 3
									061 - 076	Auto Program 4
									077 - 093	Auto Program 5
			11	20	20			56	094 - 110	Auto Program 6
									111 - 126	Auto Program 7
									127 - 143	Auto Program 8
									144 - 160	Auto Program 9
									161 - 176	Auto Program 10
									177 - 193	Auto Program 11
									194 - 210	Auto Program 12
									211 - 226	Auto Program 13
									227 - 255	No Function
			12	21	21			57	000 - 255	<i>RGB Background Programs Speed</i> , slow to fast
			13	22	22			58	000 - 255	<i>RGB Background Program Fade</i> , least to most

ADJ ELECTRAPIX PAR 7 - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
5Ch	6Ch	9Ch	13Ch	22Ch	24Ch	42Ch	45Ch	60Ch		
					23			59		<i>Dim Mode</i>
									000 - 020	Default to Unit Setting
									021 - 040	Standard
									041 - 060	Stage
									061 - 080	TV
									081 - 100	Architectural
									101 - 120	Theatre
									121 - 140	Stage 2
										<i>Dim Speed</i>
									141	0.1s
									142	0.2s
									143	0.3s
									144	0.4s
									145	0.5s
									146	0.6s
									147	0.7s
									148	0.8s
									149	0.9s
									150	1.0s
									151	1.5s
									152	2.0s
									153	3.0s
									154	4.0s
									155	5.0s
									156	6.0s
									157	7.0s
									158	8.0s
									159	9.0s
									160	10.0s
									161 - 255	Default to Unit Setting
					24			60		<i>Dim Curves</i>
									000 - 020	Square
									021 - 040	Linear
									041 - 060	Inv Squa
									061 - 080	S Curve
									081 - 255	No Function