

ADJ JOLT BAR FX2 - DMX TRAITS

CHANNEL																	DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	16 CH	18 CH	20 CH	32 CH	34 CH	38 CH	43 CH	45 CH	64 CH	78 CH	80 CH	112 CH	127 CH	129 CH		
1	1	1		1	1												000-255	Outer Red , 0% - 100%
2	2	2		2	2												000-255	Outer Green , 0% - 100%
3	3	3		3	3												000-255	Outer Blue , 0% - 100%
4	3	4															000-255	Inner White, 0% - 100%
								30	33	35		70	72				000-255	Inner White Group 1
								31	34	36		71	73				000-255	Inner White Group 2
								32	35	37		72	74				000-255	Inner White Group 3
								33	36	38		73	75				000-255	Inner White Group 4
5	5	6															000-255	Dimmer, 0% - 100%
6	6	7															000-255	Dimmer Fine, 0% - 100%
				5	7			25	26	28		65	67		98	100	000-255	Outer Dimmer, 0% - 100%
				6	8			26	27	29		66	68		99	101	000-255	Outer Dimmer Fine, 0% - 100%
	7	8																Strobe Effect
																	000-002	Open
																	003-005	Strobe
																	006-050	Ramp up
																	051-100	Ramp down
																	101-150	Ramp up-down
																	151-200	Lightning
																	201-255	Random
	8	9														000-255	Strobe Rate ,slow to fast	
	9	10															000-255	Strobe Duration ,slow to fast
		5		4	6				25	27					97	99	000-255	Outer Color Macros
				7	9			27	28	30		67	69		100	102		Outer Strobe Effect
																	000-002	Open
																	003-005	Strobe
																	006-050	Ramp up
																	051-100	Ramp down
																	101-150	Ramp up-down
																	151-200	Lightning
																	201-255	Random
				8	10			28	29	31		68	70		101	103	000-255	Outer Strobe Rate,slow to fast
				9	11			29	30	32		69	71		102	104	000-255	Outer Strobe Duration,slow to fast

ADJ JOLT BAR FX2 - DMX TRAITS

CHANNEL																	DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	16 CH	18 CH	20 CH	32 CH	34 CH	38 CH	43 CH	45 CH	64 CH	78 CH	80 CH	112 CH	127 CH	129 CH		
		11		10	12				31	33					103	105		Outer Program Macro
																	000-005	No function
																	006-015	Macro 1
																	016-025	Macro 2
																	026-035	Macro 3
																	036-045	Macro 4
																	046-055	Macro 5
																	056-065	Macro 6
																	066-075	Macro 7
																	076-085	Macro 8
																	086-095	Macro 9
																	096-105	Macro 10
																	106-115	Macro 11
																	116-125	Macro 12
																	126-135	Macro 13
																	136-145	Macro 14
																	146-155	Macro 15
																	156-165	Macro 16
																	166-175	Macro 17
																	176-185	Macro 18
																	186-195	Macro 19
																	196-205	Macro 20
																	206-215	Macro 21
																	216-225	Macro 22
																	226-235	Macro 23
236-245	Macro 24																	
246-255	Macro 25																	
				11	13				32	34					104	106	000-255	Outer Program Macro Speed
				12	14			34	37	39		74		76	121	123	000-255	Inner Dimmer, 0% - 100%
				13	15			35	38	40		75		77	122	124	000-255	Inner Dimmer Fine, 0% - 100%

ADJ JOLT BAR FX2 - DMX TRAITS

CHANNEL																	DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	16 CH	18 CH	20 CH	32 CH	34 CH	38 CH	43 CH	45 CH	64 CH	78 CH	80 CH	112 CH	127 CH	129 CH		
				14	16			36	39	41		76	78		123	125		Inner Strobe Effect
																	000-002	Open
																	003-005	Strobe
																	006-050	Ramp up
																	051-100	Ramp down
																	101-150	Ramp up-down
																	151-200	lightning
																	201-255	Random
				15	17			37	40	42		77	79		124	126	000-255	Inner Strobe Rate, slow to fast
				16	18			38	41	43		78	80		125	127	000-255	Inner Strobe Duration, slow to fast
		12		17	19				42	44					126	128		Inner Program Macro
																	000-005	No function
																	006-033	Macro 1
																	034-060	Macro 2
																	061-088	Macro 3
																	089-116	Macro 4
																	117-144	Macro 5
																	145-172	Macro 6
																	173-200	Macro 7
																	201-228	Macro 8
																	229-255	Macro 9
				18	20				43	45				127	129	000-255	Inner Program Macro Speed	
		13															000-255	In/Out Program Macro Speed, slow to fast

ADJ JOLT BAR FX2 - DMX TRAITS

CHANNEL																DMX VALUES	FUNCTION	
6 CH	9 CH	13 CH	16 CH	18 CH	20 CH	32 CH	34 CH	38 CH	43 CH	45 CH	64 CH	78 CH	80 CH	112 CH	127 CH			129 CH
			1			1	1	1	1	1	1	1	1	1	1	1	000-255	Red 1
			2			2	2	2	2	2	2	2	2	2	2	2	000-255	Green 1
			3			3	3	3	3	3	3	3	3	3	3	3	000-255	Blue 1
			4			4	4	4	4	4	4	4	4	4	4	4	000-255	Red 2
			5			5	5	5	5	5	5	5	5	5	5	5	000-255	Green 2
			6			6	6	6	6	6	6	6	6	6	6	6	000-255	Blue 2
			7			7	7	7	7	7	7	7	7	7	7	7	000-255	Red 3
			8			8	8	8	8	8	8	8	8	8	8	8	000-255	Green 3
			9			9	9	9	9	9	9	9	9	9	9	9	000-255	Blue 3
			10			10	10	10	10	10	10	10	10	10	10	10	000-255	Red 4
			11			11	11	11	11	11	11	11	11	11	11	11	000-255	Green 4
			12			12	12	12	12	12	12	12	12	12	12	12	000-255	Blue 4
						13	13	13	13	13	13	13	13	13	13	13	000-255	Red 5
						14	14	14	14	14	14	14	14	14	14	14	000-255	Green 5
						15	15	15	15	15	15	15	15	15	15	15	000-255	Blue 5
						16	16	16	16	16	16	16	16	16	16	16	000-255	Red 6
						17	17	17	17	17	17	17	17	17	17	17	000-255	Green 6
						18	18	18	18	18	18	18	18	18	18	18	000-255	Blue 6
						19	19	19	19	19	19	19	19	19	19	19	000-255	Red 7
						20	20	20	20	20	20	20	20	20	20	20	000-255	Green 7
						21	21	21	21	21	21	21	21	21	21	21	000-255	Blue 7
						22	22	22	22	22	22	22	22	22	22	22	000-255	Red 8
						23	23	23	23	23	23	23	23	23	23	23	000-255	Green 8
						24	24	24	24	24	24	24	24	24	24	24	000-255	Blue 8
											25	25	25	25	25	25	000-255	Red 9
											26	26	26	26	26	26	000-255	Green 9
											27	27	27	27	27	27	000-255	Blue 9
											28	28	28	28	28	28	000-255	Red 10
											29	29	29	29	29	29	000-255	Green 10
											30	30	30	30	30	30	000-255	Blue 10
											31	31	31	31	31	31	000-255	Red 11
											32	32	32	32	32	32	000-255	Green 11
											33	33	33	33	33	33	000-255	Blue 11
											34	34	34	34	34	34	000-255	Red 12
											35	35	35	35	35	35	000-255	Green 12
											36	36	36	36	36	36	000-255	Blue 12
											37	37	37	37	37	37	000-255	Red 13
											38	38	38	38	38	38	000-255	Green 13
											39	39	39	39	39	39	000-255	Blue 13

ADJ JOLT BAR FX2 - DMX TRAITS

CHANNEL																	DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	16 CH	18 CH	20 CH	32 CH	34 CH	38 CH	43 CH	45 CH	64 CH	78 CH	80 CH	112 CH	127 CH	129 CH		
											40	40	40	40	40	40	000-255	Red 14
											41	41	41	41	41	41	000-255	Green 14
											42	42	42	42	42	42	000-255	Blue 14
											43	43	43	43	43	43	000-255	Red 15
											44	44	44	44	44	44	000-255	Green 15
											45	45	45	45	45	45	000-255	Blue 15
											46	46	46	46	46	46	000-255	Red 16
											47	47	47	47	47	47	000-255	Green 16
											48	48	48	48	48	48	000-255	Blue 16
														49	49	49	000-255	Red 17
														50	50	50	000-255	Green 17
														51	51	51	000-255	Blue 17
														52	52	52	000-255	Red 18
														53	53	53	000-255	Green 18
														54	54	54	000-255	Blue 18
														55	55	55	000-255	Red 19
														56	56	56	000-255	Green 19
														57	57	57	000-255	Blue 19
														58	58	58	000-255	Red 20
														59	59	59	000-255	Green 20
														60	60	60	000-255	Blue 20
														61	61	61	000-255	Red 21
														62	62	62	000-255	Green 21
														63	63	63	000-255	Blue 21
														64	64	64	000-255	Red 22
														65	65	65	000-255	Green 22
														66	66	66	000-255	Blue 22
														67	67	67	000-255	Red 23
														68	68	68	000-255	Green 23
														69	69	69	000-255	Blue 23
														70	70	70	000-255	Red 24
														71	71	71	000-255	Green 24
														72	72	72	000-255	Blue 24
														73	73	73	000-255	Red 25
														74	74	74	000-255	Green 25
														75	75	75	000-255	Blue 25

ADJ JOLT BAR FX2 - DMX TRAITS

CHANNEL																	DMX VALUES	FUNCTION
6 CH	9 CH	13 CH	16 CH	18 CH	20 CH	32 CH	34 CH	38 CH	43 CH	45 CH	64 CH	78 CH	80 CH	112 CH	127 CH	129 CH		
														76	76	76	000-255	Red 26
														77	77	77	000-255	Green 26
														78	78	78	000-255	Blue26
														79	79	79	000-255	Red 27
														80	80	80	000-255	Green 27
														81	81	81	000-255	Blue 27
														82	82	82	000-255	Red 28
														83	83	83	000-255	Green 28
														84	84	84	000-255	Blue 28
														85	85	85	000-255	Red 29
														86	86	86	000-255	Green 29
														87	87	87	000-255	Blue 29
														88	88	88	000-255	Red 30
														89	89	89	000-255	Green 30
														90	90	90	000-255	Blue 30
														91	91	91	000-255	Red 31
														92	92	92	000-255	Green 31
														93	93	93	000-255	Blue 31
														94	94	94	000-255	Red 32
														95	95	95	000-255	Green 32
														96	96	96	000-255	Blue 32
					4		25			25			49			97		CT Presets
																	000-022	Open
																	023-089	CTO 2300K - 8900K
																	090-255	9000K
					5		26			26			50			98	000 - 255	Green Shift
			13			25	27				49	49	51	97	105	107	000-255	White 1
			14			26	28				50	50	52	98	106	108	000-255	White 2
			15			27	29				51	51	53	99	107	109	000-255	White 3
			16			28	30				52	52	54	100	108	110	000-255	White 4
						29	31				53	53	55	101	109	111	000-255	White 5
						30	32				54	54	56	102	110	112	000-255	White 6
						31	33				55	55	57	103	111	113	000-255	White 7
						32	34				56	56	58	104	112	114	000-255	White 8
											57	57	59	105	113	115	000-255	White 9
											58	58	60	106	114	116	000-255	White 10
											59	59	61	107	115	117	000-255	White 11
											60	60	62	108	116	118	000-255	White 12
											61	61	63	109	117	119	000-255	White 13
											62	62	64	110	118	120	000-255	White 14
											63	63	65	111	119	121	000-255	White 15
											64	64	66	112	120	122	000-255	White 16