

ADJ MINI DEKKER LZR - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTIONS
2Ch	7Ch		
1	1		Show Mode
		0 - 9	No Function
		10 - 98	Show 0 (LED, Laser, & Strobe)
		90 - 169	Show 1 (LED)
		170 - 255	Show 2 (Laser)
2			Show Speed / Sound Sensitivity
		0 - 247	Show Speed, slow to fast
		248 - 255	Sound Active
	2		RGBW Color Macro
		0 - 9	No Function
		10 - 22	Red
		23 - 35	Green
		36 - 48	Blue
		49 - 61	White
		62 - 74	Red + Green
		75 - 87	Red + Blue
		88 - 100	Red + White
		101 - 113	Green + Blue
		114 - 126	Green + White
		127 - 139	Blue + White
		140 - 152	Red + Green + Blue
		153 - 165	Red + Green + White
		166 - 178	Green + Blue + White
		179 - 191	Green + Blue + White
		192 - 198	Red + Green + Blue + White
		199 - 225	Color Fade (1 Color), slow to fast
		226 - 255	Color Fade (Mixed), slow to fast

ADJ MINI DEKKER LZR - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
2Ch	7Ch		
	3		<i>LED Strobe</i>
		0 - 9	Strobe Off
		10 - 244	Strobing, slow to fast
		245 - 255	Sound Active Strobe
	4		<i>Laser Color Control</i>
		0 - 9	Laser Off
		10 - 49	Red
		50 - 89	Green
		90 - 129	Red & Green
		130 - 169	Red On, Green Flash
		170 - 209	Green On, Red Flash
		210 - 249	Red & Green Flash
		250 - 255	Red & Green Alternate Flash
	5		<i>Laser Strobing</i>
		0 - 244	Strobing, slow to fast
		245 - 255	Sound Active Strobe
	6		<i>LED Motor Control</i>
		0 - 127	Select Motor Position
		128 - 255	Rotation, slow to fast
	7		<i>Laser Motor Control</i>
		0 - 127	Laser Patterns
		128 - 255	Pattern Chase, slow to fast