

ADJ PAR Z150 RGBA - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
4Ch	5Ch	6Ch	7Ch	8Ch	9Ch	10Ch	11Ch	12Ch		
1	1	1	1	1	1	1	1	1	0 - 255	<i>Red</i>
2	2	2	2	2	2	2	2	2	0 - 255	<i>Green</i>
3	3	3	3	3	3	3	3	3	0 - 255	<i>Blue</i>
4	4	4	4	4	4	4	4	4	0 - 255	<i>Amber</i>
				5	5	5	5	5	0 - 255	<i>Color Macros</i> , refer to Color Macros Table sec- tion
					6	6	6	6	0 - 255	<i>Color Temperature Lin- ear</i> , 2300K - 9900K
										<i>Color Temperature Pre- sets</i>
									0 - 22	Open
									23	2300K
									24	2400K
									25	2500K
									26	2600K
									27	2700K
									28	2800K
									29	2900K
									30	3000K
									31	3100K
									32	3200K
									33	3300K
									34	3400K
									35	3500K
									36	3600K
									37	3700K
									38	3800K
									39	3900K
									40	4000K
									41	4100K
									42	4200K
									43	4300K
									44	4400K
									45	4500K
									46	4600K
									47	4700K

ADJ PAR Z150 RGBA - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
4Ch	5Ch	6Ch	7Ch	8Ch	9Ch	10Ch	11Ch	12Ch		
						7	7	7		<i>Color Temperature Pre-sets (continued)</i>
									48	4800K
									49	4900K
									50	5000K
									51	5100K
									52	5200K
									53	5300K
									54	5400K
									55	5500K
									56	5600K
									57	5700K
									58	5800K
									59	5900K
									60	6000K
									61	6100K
									62	6200K
									63	6300K
									64	6400K
						65	6500K			
						66	6600K			
						67	6700K			
						68	6800K			
						69	6900K			
						70	7000K			
						71	7100K			
						72	7200K			
						73	7300K			
						74	7400K			
						75	7500K			
						76	7600K			
						77	7700K			
						78	7800K			
						79	7900K			
						80	8000K			
						81	8100K			
						82	8200K			

ADJ PAR Z150 RGBA - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
4Ch	5Ch	6Ch	7Ch	8Ch	9Ch	10Ch	11Ch	12Ch		
						7	7	7		<i>Color Temperature Pre-sets (continued)</i>
									83	8300K
									84	8400K
									85	8500K
									86	8600K
									87	8700K
									88	8800K
									89	8900K
									90	9000K
									91	9100K
									92	9200K
									93	9300K
									94	9400K
									95	9500K
									96	9600K
									97	9700K
									98	9800K
									99	9900K
									100 - 255	No Function
			5	6	7	8	8	8		<i>Strobe</i>
									0 - 31	LED Off
									32 - 63	LED On
									64 - 95	Strobe, slow > fast
									96 - 127	LED On
									128 - 159	Pulse Strobe, slow > fast
									160 - 191	LED On
									192 - 223	Random Strobe, slow > fast
									224 - 255	LED On
	5	5	6	7	8	9	9	9	0 - 255	<i>Dimmer</i>
		6	7	8	9	10	10	10	0 - 255	<i>Dimmer Fine</i>

ADJ PAR Z150 RGBA - DMX TRAITS

CHANNEL									DMX VALUES	FUNCTION
4Ch	5Ch	6Ch	7Ch	8Ch	9Ch	10Ch	11Ch	12Ch		
								11		<i>Dim Modes</i>
									0 - 20	Standard
									21 - 40	Stage
									41 - 60	TV
									61 - 80	Architectural
									81 - 100	Theatre
									101 - 120	Stage 2
									121 - 255	Default to Unit Setting
							11	12		<i>Dim Curves</i>
									0 - 20	Square
									21 - 40	Linear
									41 - 60	Inv Squa
									61 - 80	S Curve
									81 - 255	No Function