

ADJ PAR Z150 RGBA PLUS - DMX TRAITS

4Ch	5Ch	9Ch-A	9Ch-B	13Ch	15Ch	DMX VALUES	FUNCTION
1		1		1	1		Red
						0-255	0 - 100%
2		2		2	2		Green
						0-255	0 - 100%
3		3		3	3		Blue
						0-255	0 - 100%
4		4		4	4		Amber
						0-255	0 - 100%
		5	1	5	5		Color Macros
						0-255	See Color Macros Chart
	1	6	2	6	6		Color Temperature
						0-255	2300-9900K Linear
	2	7	3	7	7		White Color Temperature Presets
						0-22	Open
						23	2300K
						24	2400K
						25	2500K
						26	2600K
						27	2700K
						28	2800K
						29	2900K
						30	3000K
						31	3100K
						32	3200K
						33	3300K
						34	3400K
						35	3500K
						36	3600K
						37	3700K
						38	3800K
						39	3900K
						40	4000K
						41	4100K
						42	4200K
						43	4300K

ADJ PAR Z150 RGBA PLUS - DMX TRAITS

4Ch	5Ch	9Ch-A	9Ch-B	13Ch	15Ch	DMX VALUES	FUNCTION
	2	7	3	7	7		White Color Temperature Presets (continued)
						44	4400K
						45	4500K
						46	4600K
						47	4700K
						48	4800K
						49	4900K
						50	5000K
						51	5100K
						52	5200K
						53	5300K
						54	5400K
						55	5500K
						56	5600K
						57	5700K
						58	5800K
						59	5900K
						60	6000K
						61	6100K
						62	6200K
						63	6300K
						64	6400K
						65	6500K
						66	6600K
						67	6700K
						68	6800K
						69	6900K
						70	7000K
						71	7100K
						72	7200K
						73	7300K
						74	7400K
						75	7500K
						76	7600K

ADJ PAR Z150 RGBA PLUS - DMX TRAITS

4Ch	5Ch	9Ch-A	9Ch-B	13Ch	15Ch	DMX VALUES	FUNCTION
	2	7	3	7	7		White Color Temperature Presets (continued)
						77	7700K
						78	7800K
						79	7900K
						80	8000K
						81	8100K
						82	8200K
						83	8300K
						84	8400K
						85	8500K
						86	8600K
						87	8700K
						88	8800K
						89	8900K
						90	9000K
						91	9100K
						92	9200K
						93	9300K
						94	9400K
						95	9500K
						96	9600K
						97	9700K
						98	9800K
						99	9900K
						100-255	No Function
	3	8	4	8	8		Shutter
						0-31	LEDs Off
						32-63	LEDs On
						64-95	Strobe Effect, slow to fast
						96-127	LEDs On
						128-159	Pulse Effect in Sequences
						160-191	LEDs On
						192-223	Random Strobe Effect, slow to fast
						224-255	LEDs On

ADJ PAR Z150 RGBA PLUS - DMX TRAITS

4Ch	5Ch	9Ch-A	9Ch-B	13Ch	15Ch	DMX VALUES	FUNCTION
	4	9	5	9	9		Dimmer
						0-255	Intensity, 0-100%
	5		6	10	10		Dimmer Fine
						0-255	Dimmer fine adjustment
							Internal Programs
						0-10	Off
						11-26	Auto Program 1
						27-43	Auto Program 2
						44-60	Auto Program 3
						61-76	Auto Program 4
						77-93	Auto Program 5
						94-110	Auto Program 6
						111-126	Auto Program 7
						127-143	Auto Program 8
						144-160	Auto Program 9
						161-176	Auto Program 10
						177-193	Auto Program 11
						194-210	Auto Program 1
						211-226	Auto Program 1
						227-255	No Function
							Internal Programs Speed
						0-255	Slow to fast
							Internal Programs Fade
						0-255	Least fade to most fade
							Dim Mode
						0-20	Default to Unit Setting
						21-40	Standard
						41-60	Stage
						61-80	TV
						81-100	Architectural
						101-120	Theatre
						121-140	Stage 2

ADJ PAR Z150 RGBA PLUS - DMX TRAITS

4Ch	5Ch	9Ch-A	9Ch-B	13Ch	15Ch	DMX VALUES	FUNCTION
					14		Dim Speed
						141	0.1s
						142	0.2s
						143	0.3s
						144	0.4s
						145	0.5s
						146	0.6s
						147	0.7s
						148	0.8s
						149	0.9s
						150	1.0s
						151	1.5s
						152	2.0s
						153	3.0s
						154	4.0s
						155	5.0s
						156	6.0s
						157	7.0s
						158	8.0s
						159	9.0s
						160	10s
						161-255	Default to Unit Setting
					15		Dim Curves
						0-20	Square
						21-40	Linear
						41-60	Inv Square
						61-80	S Curve
						81-255	No Function