

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice				
MODE/CHANNELS			VALUES	FUNCTION
4ch	13ch	209ch		
1	1			Amber All
			000 - 255	0% to 100%
		1		Amber 1
			000 - 255	0% to 100%
		2		Amber 2
			000 - 255	0% to 100%
		3		Amber 3
			000 - 255	0% to 100%
		4		Amber 4
			000 - 255	0% to 100%
		5		Amber 5
			000 - 255	0% to 100%
		6		Amber 6
			000 - 255	0% to 100%
		7		Amber 7
			000 - 255	0% to 100%
	2	8		Amber Shutter
			000 - 031	Shutter Closed (LEDs Off)
			032 - 063	Shutter Open (LEDs On)
			064 - 095	Strobe Effect, slow to fast
			096 - 127	Shutter Open (LEDs On)
			128 - 159	Pulse Effect in Sequences
			160 - 191	Shutter Open (LEDs On)
			192 - 223	Random Strobe Effect, slow to fast
			224 - 255	Shutter Open (LEDs On)
	3	9		Amber Dimmer
			000 - 255	0% to 100%
2	4			Outer Red All
			000 - 255	0% to 100%
3	5			Outer Green All
			000 - 255	0% to 100%
4	6			Outer Blue All
			000 - 255	0% to 100%

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice				
MODE/CHANNELS			VALUES	FUNCTION
4ch	13ch	209ch		
		10		Outer 1 Red
			000 - 255	0% to 100%
		11		Outer 1 Green
			000 - 255	0% to 100%
		12		Outer 1 Blue
			000 - 255	0% to 100%
...	...	...	...	...
		205		Outer 66 Red
			000 - 255	0% to 100%
		206		Outer 66 Green
			000 - 255	0% to 100%
		207		Outer 66 Blue
			000 - 255	0% to 100%
	7	208		Outer Shutter
			000 - 031	Shutter Closed (LEDs Off)
			032 - 063	Shutter Open (LEDs On)
			064 - 095	Strobe Effect, slow to fast
			096 - 127	Shutter Open (LEDs On)
			128 - 159	Pulse Effect in Sequences
			160 - 191	Shutter Open (LEDs On)
			192 - 223	Random Strobe Effect, slow to fast
			224 - 255	Shutter Open (LEDs On)
	8	209		Outer Dimmer
			000 - 255	0% to 100%
	9			Color Macros
			000 - 255	See Color Macros Chart
	10			Amber Programs
			000 - 006	Off
			007 - 013	Program 1
			014 - 019	Program 2
			020 - 026	Program 3
			027 - 032	Program 4
			033 - 039	Program 5
			040 - 045	Program 6
			046 - 052	Program 7
			053 - 058	Program 8

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice				
MODE/CHANNELS			VALUES	FUNCTION
4ch	13ch	209ch		
	10			Amber Programs (continued)
			059 - 065	Program 9
			066 - 071	Program 10
			072 - 078	Program 11
			079 - 084	Program 12
			085 - 091	Program 13
			092 - 097	Program 14
			098 - 104	Program 15
			105 - 111	Program 16
			112 - 117	Program 17
			118 - 124	Program 18
			125 - 130	Program 19
			131 - 137	Program 20
			138 - 143	Program 21
			144 - 150	Program 22
			151 - 156	Program 23
			157 - 163	Program 24
			164 - 169	Program 25
			170 - 176	Program 26
			177 - 182	Program 27
			183 - 189	Program 28
			190 - 195	Program 29
			196 - 202	Program 30
			203 - 208	Program 31
			209 - 215	Program 32
			216 - 222	Program 33
			223 - 228	Program 34
			229 - 235	Program 35
			236 - 241	Program 36
			242 - 248	Program 37
			249 - 254	Program 38
			255	Program 39
	11			Amber Program Speed
			000 - 255	Slow to fast

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice				
MODE/CHANNELS			VALUES	FUNCTION
4ch	13ch	209ch		
	12			RGB Programs
			000 - 001	Program 0
			002 - 003	Program 1
			004 - 005	Program 2
			...	...
			252 - 253	Program 126
			254 - 255	Program 127
	13			RGB Program Speed
			000 - 255	Slow to fast