

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice							
MODE/CHANNELS						VALUES	FUNCTION
4ch	13ch	44ch	77ch	110ch	209ch		
1	1						Amber All
						000 - 255	0% to 100%
		1	1	1	1		Amber 1
						000 - 255	0% to 100%
		2	2	2	2		Amber 2
						000 - 255	0% to 100%
		3	3	3	3		Amber 3
						000 - 255	0% to 100%
		4	4	4	4		Amber 4
						000 - 255	0% to 100%
		5	5	5	5		Amber 5
						000 - 255	0% to 100%
		6	6	6	6		Amber 6
						000 - 255	0% to 100%
		7	7	7	7		Amber 7
						000 - 255	0% to 100%
	2	8	8	8	8		Amber Shutter
						000 - 031	Shutter Closed (LEDs Off)
						032 - 063	Shutter Open (LEDs On)
						064 - 095	Strobe Effect, slow to fast
						096 - 127	Shutter Open (LEDs On)
						128 - 159	Pulse Effect in Sequences
						160 - 191	Shutter Open (LEDs On)
						192 - 223	Random Strobe Effect, slow to fast
	3	9	9	9	9		Amber Dimmer
						000 - 255	0% to 100%
2	4						Outer Red All
						000 - 255	0% to 100%
3	5						Outer Green All
						000 - 255	0% to 100%
4	6						Outer Blue All
						000 - 255	0% to 100%

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice							
MODE/CHANNELS						VALUES	FUNCTION
4ch	13ch	44ch	77ch	110ch	209ch		
		10	10	10	10		Outer 1 Red
						000 - 255	0% to 100%
		11	11	11	11		Outer 1 Green
						000 - 255	0% to 100%
		12	12	12	12		Outer 1 Blue
						000 - 255	0% to 100%
		...	...	...	...	...	...
		40	40	40	40		Outer 11 Red
						000 - 255	0% to 100%
		41	41	41	41		Outer 11 Green
						000 - 255	0% to 100%
		42	42	42	42		Outer 11 Blue
						000 - 255	0% to 100%
			...	...	...	...	...
			73	73	73		Outer 22 Red
						000 - 255	0% to 100%
			74	74	74		Outer 22 Green
						000 - 255	0% to 100%
			75	75	75		Outer 22 Blue
						000 - 255	0% to 100%
				...	...	...	...
				106	106		Outer 33 Red
						000 - 255	0% to 100%
				107	107		Outer 33 Green
						000 - 255	0% to 100%
				108	108		Outer 33 Blue
						000 - 255	0% to 100%
					...	...	...
					205		Outer 66 Red
						000 - 255	0% to 100%
					206		Outer 66 Green
						000 - 255	0% to 100%
					207		Outer 66 Blue
						000 - 255	0% to 100%

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice							
MODE/CHANNELS						VALUES	FUNCTION
4ch	13ch	44ch	77ch	110ch	209ch		
	7	43	76	109	208		Outer Shutter
						000 - 031	Shutter Closed (LEDs Off)
						032 - 063	Shutter Open (LEDs On)
						064 - 095	Strobe Effect, slow to fast
						096 - 127	Shutter Open (LEDs On)
						128 - 159	Pulse Effect in Sequences
						160 - 191	Shutter Open (LEDs On)
						192 - 223	Random Strobe Effect, slow to fast
						224 - 255	Shutter Open (LEDs On)
	8	44	77	110	209		Outer Dimmer
						000 - 255	0% to 100%
	9						Color Macros
						000 - 255	See Color Macros Chart
	10						Amber Programs
						000 - 006	Off
						007 - 013	Program 1
						014 - 019	Program 2
						020 - 026	Program 3
						027 - 032	Program 4
						033 - 039	Program 5
						040 - 045	Program 6
						046 - 052	Program 7
						053 - 058	Program 8
						059 - 065	Program 9
						066 - 071	Program 10
						072 - 078	Program 11
						079 - 084	Program 12
						085 - 091	Program 13
						092 - 097	Program 14
						098 - 104	Program 15
						105 - 111	Program 16
						112 - 117	Program 17
						118 - 124	Program 18
						125 - 130	Program 19
						131 - 137	Program 20
						138 - 143	Program 21

ELIMINATOR ELEKTRON BAR FX - DMX TRAITS

Features subject to change without notice							
MODE/CHANNELS						VALUES	FUNCTION
4ch	13ch				209ch		
	10						Amber Programs(continued)
						144 - 150	Program 22
						151 - 156	Program 23
						157 - 163	Program 24
						164 - 169	Program 25
						170 - 176	Program 26
						177 - 182	Program 27
						183 - 189	Program 28
						190 - 195	Program 29
						196 - 202	Program 30
						203 - 208	Program 31
						209 - 215	Program 32
						216 - 222	Program 33
						223 - 228	Program 34
						229 - 235	Program 35
						236 - 241	Program 36
						242 - 248	Program 37
						249 - 254	Program 38
						255	Program 39
	11						Amber Program Speed
						000 - 255	Slow to fast
	12						Outer Internal Programs
						000 - 001	Program 0
						002 - 003	Program 1
						004 - 005	Program 2
						...	...
						252 - 253	Program 126
						254 - 255	Program 127
	13						Outer Program Speed
						000 - 255	Slow to fast