


# PAR Z MOVE

200W COB (Chip on Board) Warm white (3000K) LED on a moving head base

The Par Z Move is the next generation fixture in ADJ's popular PAR Z100 Series of C.OB. LED Pars. It's powered by a high output 200W C.O.B. (Chip on Board) warm white LED on a moving head base. Featuring motorized zoom (9 ~ 43-degrees) and 0-100% dimming plus 16-bit fine dimming for stages, theaters, churches, nightclubs, concert venues and event productions.

There are a variety of professional features such as: DMX and RDM control, pan & fine pan, tilt & fine tilt and a color display with 4 buttons to easily access all the built-in functions. Locking power In/Out to daisy chain the power and 3-pin and 5-pin XLR, DMX In/Out give lighting designers the best, most reliable connections on the market. There is also a built-in USB port to easily update the software if needed.





# PAR Z MOVE



## **Optical:**

- 200W Warm White COB (Chip On Board) LED engine (3000K)
- Motorized Zoom: 9 ~ 43-degrees
- CRI: 96
- 15391 LUX @ 1M; 616 LUX @ 5M (zoomed out)
- 234685 LUX @ 1M; 9387 LUX @ 5M (zoomed in)

#### **Connections:**

- Locking power In/Out to daisy chain power
- 3-pin & 5-pin XLR, In/Out DMX Connections
- Built-in USB software upgrade port
- With Wired Digital Communication Network

#### **Control:**

- 3 DMX Channel Modes: 7, 9, & 11-channels
- Color display with touch button
- DMX-512 & RDM
- Pan: 540-degrees (plus 16-bit Fine Pan)
- Tilt: 200-degrees (plus 16-bit Fine Tilt)
- 6 Dimmer Curve Modes + 16-bit Fine Dimming
- Strobe & Shutter Control

#### **Electrical:**

- Multi-voltage operation: 100-240V, 50/60Hz
- Power Consumption: 233W max
- With Wired Digital Communication Network
- cETLus Approved (Control #4000358)

### **Dimensions / Weight:**

- Dimensions (LxWxH): 12.05" x 8.6" x 17.63" / 306x218x448mm
- Weight: 25 lbs. / 11.3 kg.

#### What's In The Box:

- Two Omega Brackets
- Locking power cable





