

*American DJ®*

USER

# Instructions

## **PDP-800™**



**Caution!** Always disconnect from main power before replacing lamps or servicing unit. Remember to always replace with same lamps and fuses.

**Model: PDP-800™**

### **SPECIFICATIONS:**

Protection: 20A breaker

Power: 110V/60Hz

Weight: 7 lbs.

Size: 19" x 6.75" x 1.75"

19 in. single space rack mount.

Thank you for purchasing this American DJ® product. For your convenience this products ready to be used, there is no assembly required. Please read the following instructions before installing or using your new unit.

### **Operating Instructions:**

The American DJ® PDP-800™ Power Distribution Panel features include: The PDP-800™ features 7 protected switched A/C grounded outlets on the rear of the unit, & 1 A/C unswitched outlet on the rear of the unit, 1 A/C outlet switched on the front panel, 15 amps per outlet/20A protection breaker button on the front panel, master on/off switch, and dual pop-out lights with dim control knob; great for lighting up DJ control booths. The PDP-800™ eliminates wires in mobile racks, control booths, or studios. For night club, studios, and mobile DJ's where power distribution is a concern. Single space 19" rack amount.

**NOTICE:** When pop-up lights are not in use make sure dim control knob is all the way off.

For service, contact your *American DJ®* dealer.

*American DJ®* LOS ANGELES, CA. 90058