

# American DJ® User Instructions

---

## PDP-900™



**Caution!** Always disconnect from main power before replacing lamps or servicing unit. Remember to always replace with same lamps and fuses.

**Model: PDP-900™**

### SPECIFICATIONS:

Protection: 20A breaker

Power: 110V/60Hz

Weight: 7 lbs.

Size: 19" x 6.75" x 1.75"

19 in. single space rack mount.

Thank you for purchasing this *American DJ®* product. For your convenience this products ready to be used, there is no assembly required. Please read the following instructions before installing or using your new unit.

### Operating Instructions:

The American DJ® PDP-900™ protects your equipment from voltage surges! A power surge & spike protector, with A/C filter for unwanted RFI noise. **With special feature: digital voltage meter.** The PDP-900™ also features 7 protected switched A/C grounded outlets on rear of unit, & 1 A/C unswitched outlet on rear of unit, 1 A/C outlet switched on front of panel, 15 amps per outlet/20A protection breaker button on front panel, master on/off switch, and dual pop-out lights with dim control knob; great for lighting up DJ control booths. The PDP-900™ eliminates wires in mobile racks, control booths, or studios. For night club, studios, and mobile DJ's where power distribution is a concern. Single space 19 inch rack mount.

**NOTICE:** When pop-up lights are not in use make sure dim control knob is all the way off.

For service, contact your *American DJ®* dealer.

*American DJ®* LOS ANGELES, CA. 90058