temerican L



User Instructions

Los Angeles Ca. 90058 www.americandj.com 4295 Charter Street Humerican DI

Reflections II™

Introduction

damage and be sure all equipment necessary to operate the system carton appears to be damaged, carefully inspect your fixture for any can DJ_®. Every Reflections II™ has been thoroughly tested and has ther instructions missing, please contact our toll free customer support number for furhas arrived intact. In the event damage has been found or parts are ping carton for damage that may have occurred during shipping. If the been shipped in perfect operating condition. Carefully check the ship-Unpacking: Thank you for purchasing the Reflections II™ by Ameri-

without strong flashing lights or fog. demands of theatrical groups and those that desire an incredible effect can also simulate fire. The Reflections II™ was created to meet the ulates rippling water and when used with a yellow or red gel this unit Introduction: The American DJ® Reflections IITM is an effect that sim-

also visit us on the web at www.americandj.com for any comments or 5:00 p.m. Pacific Standard Time. suggestions. Service Hours are Monday through Friday 9:00 a.m. to you encounter problems during your set up or initial operation. You may port line, to provide set up help and to answer any question should Customer Support: American DJ® provides a toll free customer sup-

Voice:

Fax: (800) 322-6337 (323) 582-2610

E-mail: support@americandj.com

not expose this unit to rain or moisture. Warning! To prevent or reduce the risk of electrical shock or fire, do

your nearest American DJ® dealer. ranty. In the unlikely event your unit may require service please contact attempt any repairs yourself, doing so will void your manufactures war-Caution! There are no user serviceable parts inside this unit. Do not

electric shock and will void the manufactures warranty different type fuse from that which is recommended may cause fire or of 2 amps is reached. If the fuse needs replacement, always replace Safety Issues: This unit may blow a fuse if the maximum allotted load instructed by an authorized American DJ_® service technician. Use of a the fuse with same exact type that was remove, unless otherwise

Reflections IITM

Safety Precautions

- To reduce the risk of electrical shock or fire, do not expose this unit rain or moisture
- Do not spill water or other liquids into or on to your unit
- Be sure that the local power outlet match that of the required voltage for your unit
- Do not attempt to operate this unit if the power cord has been frayed or broken
- shock and fire in case of an internal short Do not attempt to remove or break off the ground prong from the electrical cord. This prong is used to reduce the risk of electrical
- Disconnect from main power before making any type of connection
- Do not remove the cover under any conditions. There are no user serviceable parts inside
- Never operate this unit when it's cover is removed
- Never plug this unit in to a dimmer pack
- Do not attempt to operate this unit, if it becomes damaged
- voids all warranties This unit is intended for indoor use only, use of this product outdoors
- During long periods of non-use, disconnect the unit's main power
- Always mount this unit in safe and stable matter
- pinched by items placed upon or against them. Power cords should be routed so they are not likely to be walked on,
- Cleaning -The fixture should be cleaned only as recommended by the manufacturer. See page 5 for cleaning details.
- This unit should be situated away from heat sources such as radiadevice and a wall. that will allow proper ventilation. Allow about 6" (15 cm) between this that produce heat. Always be sure to mount this unit in an area tors, heat registers, stoves, or other appliances (including amplifiers)
- The fixture should be serviced by qualified service personnel when: A. The power-supply cord or the plug has been damaged
- B. Objects have fallen, or liquid has been spilled into the appliance
- C. The appliance has been exposed to rain or water.
- D. The appliance does not appear to operate normally or exhibits a marked change in performance

Reflections II™

General Instructions

of this unit. These instructions contain important safety information ing instructions carefully to familiarize yourself with the basic operations manual with the unit, for future reference To optimize the performance of this product, please read these operatregarding the use and maintenance of this unit. Please keep this

Reflections II™ Features

- Micro-Stepping Motors for Smooth Movement
- Full Focusing
- Fan Cooled
- Easy Lamp Replacement
- Long Life ZB-JCR H5 (15v/150w) Lamp 500 Hours
- **Light Weight Compact Design**
- Low Power Consumption

Reflections II™

Set-Up/Operation

voltage in your area matches the required voltage for your American Power Supply: Before plugging your unit in, be sure the source DJ_® Reflections II™ before attempting operation.

General Operation:

shaped lenses will spin back and forth to an audio source. The unit electrical outlet. After plugging this fixture in, the units "Reflections II™ special effects smoke. This will enhance the effects by allowing you after plugging the unit in there is no lamp output check the fuse and will react to the low frequencies of music via its internal microphone. the unit should automatically turn on after plugging the unit in to an unit is ready to be plugged in out of the box. Plug the unit's power cord with a lamp and is ready to be hung or set on a flat surface, there is to see the beams of light. in to a standard 110v~120v electrical outlet. There is no power switch, no assembly necessary and no need of a controller of any type. The to low frequencies of an audio source. The unit has been equipped This fixture is designed to operate as a stand alone unit, it will react for further instructions. For best results, we suggest using with fog or lamp. If the fuse and lamp are good, please contact customer support The audio sensitivity is preset there no need for any adjustments. If

cycle to this unit. A duty cycle is a recommended operating cycle consecutive minutes the unit operates the unit should be shut down minutes off for every 20 minutes of activity. This means for every 20 associated with a fixture. The duty cycle assigned to this unit is 10 prolong the lamp life and ensure fixture longevity. for 10 consecutive minutes. Following the prescribed duty cycle will in the unit during normal operation, it is necessary to assign a duty Duty Cycle: Because of the high temperature that may build up

> unit and will void the manufactures warranty. unless otherwise specified by an authorized American DJ® technician. Replacing with anything other than the specified part can damage the Caution: Always replace with the exact same type lamp and fuse,

Reflections II™ Cleaning

to use the unit may cause serious damage. instructions, you may have to return the unit for servicing. Continuing to blow, STOP using the unit. Contact customer support for further Warning: If, after replacing the lamp or fuse either one continues

dust, dew). In heavy club use we recommend cleaning on a monthly basis. Periodic cleaning will ensure longevity, and crisp output. the environment in which the fixture operates (I.e. smoke, fog residue, periodically to optimize light output. Cleaning frequency depends on internal and external optical lenses and mirror should be carried out Fixture Cleaning: Due to fog residue, smoke, and dust cleaning the

> fuse and discard it. Replace the fuse with the same type. Insert the a standard flat head screw driver in to the fuse holder housing. Turn Fuse Replacement: Disconnect the unit's main power supply. Insert fuse holder back into it's housing and turn it in clockwise direction to holder. Remove the fuse holder to expose the fuse. Remove the old the screwdriver in counter-clockwise direction to remove the fuse lock the holder in place.

Use normal glass cleaner and a soft cloth to wipe down the outside

allow the unit ample time to cool before attempting to replace the while the fixture is plugged in. Always disconnect the main power and lamp. Lamp replacement has been made simple by incorporating the Lamp Replacement: Caution! Never attempt to change the lamp

- ώ Use a brush to wipe down the cooling vents and fan grill.

 Clean the external lens with glass cleaner and a soft cloth every
- use of a removable lamp cover retained by a two thumb screws. 1. Be sure to follow the proper handling procedures that deal
- 4. Clean the internal lens with glass cleaner and a soft cloth every 30-60 days.

20 days.


Remove the two thumb screws located on top of the unit. These with halogen lamps.

Ņ

- Ŋ Always be sure to dry all parts completely before plugging the unit back in.
 - screw hold the lamp socket cover in place.
- Remove the lamp cover and put aside.
- 4. Carefully remove the old lamp and discard it in the trash
- Ò Replace the lamp with an exact match and reassemble

Reflections IITM

Warranty Registration



service items whether under warranty or not, must be freight pre-paid

the enclosed warranty card to validate your purchase. All returned

The Reflections II™ carries a 90 day limited warranty. Please fill out

under warranty you must provide a copy of your proof of purchase and accompany a return authorization (R.A.) number. If the unit is

invoice. Please contact American DJ® customer support for a R.A

Halogen Lamp Warning:

covered under warranty conditions. had ample time to cool. Remember, lamps are not Also, never move the fixture until the lamp has as the oil from your hands will shorten lamp life dled. Never touch the lamp with your bare fingers is highly susceptible to damage if improperly han-This fixture is fitted with a halogen lamp which

©American DJ Supply® - www.americandj.com - Reflections II™ Instruction Manual Page 5

©American DJ Supply® - www.americandj.com - Reflections II™ Instruction Manual Page 6

Reflections IITM

Warranty

90 DAY LIMITED WARRANTY

- date of purchase. This warranty shall be valid only if the product is purchased within the A. American DJ® hereby warrants, to the original purchaser, American DJ® products to be ity to establish the date and place of purchase by acceptable evidence, at the time service United States of America, including possessions and territories. It is the owner's responsibilities free of manufacturing defects in material and workmanship for a period of 90 days from the
- shipped in its original package. No accessories should be shipped with the product. If any are within the terms of this warranty, American DJ® will pay return shipping charges only charges must be pre-paid. If the requested repairs or service (including parts replacement) accessories are shipped with the product, American DJ® shall have no liability whatsoever B. For warranty service, send the product only to the American DJ® factory. All shipping for loss of or damage to any such accessories, nor for the safe return thereof to a designated point within the United States. If the entire instrument is sent, it must be
- can DJ@; if the product is damaged because not properly maintained as set forth in the is modified in any manner which American DJ® concludes, after inspection, affects the reli-C. This warranty is void if the serial number has been altered or removed; if the product instruction manual American DJ® factory unless prior written authorization was issued to purchaser by Ameriability of the product; if the product has been repaired or serviced by anyone other than the
- parts at its expense, and will absorb all expenses for warranty service and repair labor by manufactured after January 1, 1990, and bear identifying marks to that effect parts, at the sole discretion of American DJ⊚. All products covered by this warranty were this warranty shall be limited to the repair of the product, or replacement thereof, including reason of defects in material or workmanship. The sole responsibility of American DJ® under or periodic check-up. During the period specified above, American DJ® will replace defective This is not a service contract, and this warranty does not include maintenance, cleaning
- its products without any obligation to include these changes in any products theretofore E. American DJ® reserves the right to make changes in design and/or improvements upon
- chantability or fitness, shall apply to this product after said period has expired. The conprovided above; and under no circumstances shall American DJ® be liable for any loss or sumer's and or Dealer's sole remedy shall be such repair or replacement as is expressly warranties of merchantability or fitness, are limited in duration to the warranty period set sory supplied with products described above. Except to the extent prohibited by applicable F. No warranty, whether expressed or implied, is given or made with respect to any accesdamage, direct or consequential, arising out of the use of, or inability to use, this product. forth above. And no warranties, whether expressed or implied, including warranties of merlaw, all implied warranties made by American DJ⊚ in connection with this product, including
- supersedes all prior warranties and written descriptions of warranty terms and conditions G. This warranty is the only written warranty applicable to American DJ® Products and heretofore published
- H. Lamps are not covered under this or any other warranty either written or implied

©American DJ Supply® - www.americandj.com - Reflections II™ Instruction Manual Page 7

Technical Specifications:

Model: Reflections II™

Voltage: Lamps: ZB-JCR/H5 15V/150W

Dimensions:

Colors

Fuse: Weight:

Duty Cycle:

Working Position:

Warranty:

4H x 7 3/4W x 6 1/4L 120v/60Hz

White 5 Lbs.

2 Amp GMA

Any Safe, Secure Position 20 min. on/10 min. off

90 Days

prior written notice. of this unit and this manual are subject to change without any Please Note: Specifications and improvements in the design

American DJ Supply Group of Companies World Headquarters ©American DJ Supply

4295 Charter Street Los Angeles, CA 90058 USA Tel: 323-582-2650 Fax: 323-582-2610

Web: www.americandj.com E-mail: info@americandj.com