



PAR Z MOVE RGBW

300W COB (Chip on Board) RGBW LED
on a moving head base

The Par Z Move RGBW is the next generation fixture in ADJ's popular PAR Z100 Series of C.O.B. LED Pars. It's powered by a high output 300W C.O.B. (Chip on Board) RGBW LED on a moving head base. Featuring motorized zoom (9 ~ 37-degrees) and 0-100% dimming for key lighting or color washing stages, theaters, churches, nightclubs, concert venues and event productions.

There are a variety of professional features such as: DMX and RDM control, pan & fine pan, tilt & fine tilt and a color display with 4 buttons to easily access all the built-in functions. Seetronic locking power In/Out to daisy chain the power and 3-pin and 5-pin XLR, DMX In/Out give lighting designers the best, most reliable connections on the market. There is also a built-in USB port to easily update the software if needed.



PAR Z MOVE RGBW



Optical:

- 300W RGBW COB (Chip On Board) 4-IN-1 LED engine (Red, Green, Blue & White)
- 20,000 hour LED life
- Motorized Zoom: 9 ~ 37-degrees
- CRI: 80

Connections:

- Seetronic locking power In/Out to daisy chain power
- Daisy chain up to 4 fixtures @ 120V, 8 fixtures @ 230V
- 3-pin & 5-pin XLR, In/Out DMX Connections
- Built-in USB software upgrade port
- With Wired Digital Communication Network

Control:

- 3 DMX Channel Modes: 13, 15, & 16-channels
- Color display with touch button
- DMX-512 & RDM
- Pan: 540-degrees (plus 16-bit Fine Pan)
- Tilt: 200-degrees (plus 16-bit Fine Tilt)
- 0-100% Dimming

Electrical:

- Multi-voltage operation: 100-240V, 50/60Hz
- Power Consumption: 252W max
- With Wired Digital Communication Network

Dimensions / Weight:

- Dimensions (LxWxH): 12.05" x 8.6" x 17.63" / 306x218x448mm
- Weight: 25 lbs. / 11.3 kg.

What's In The Box:

- Two Omega Brackets
- Seetronic locking power cable

