

PIXEL PULSE BAR™



Add more creativity to your lightshow with the ADJ Pixel Pulse Bar. This fixture features fifteen 3-Watt 3-in-1 RGB TRI LEDs, and 5-Zones of pixel control that allow users to highlight five different colors on the fixture.

The Pixel Pulse Bar is a versatile effect any lighting designer or entertainer should have in their lighting arsenal. It can be used as a color wash, color strobe or pulse in a 5-Zone color pixel controlled light show.

The Zone chase effect gives lighting designers the ability to display this strobe/wash fixture vertical or horizontal creating chasing RGB mixed colored lighting for a dynamic energy-driven light show.

The Pixel Pulse Bar offers full DMX control with 3 DMX channel modes, dimming, strobe speed and chase speed. Users can also run the Pixel Pulse Bar in sound active mode using the exciting built-in programs or control the fixture with the easy-to-use UC3 hand-held Control

Specifications:

- LED Color Strobe/Wash effect with 5-Zone Pixel Control
- 15x 3-Watt 3-in-1 RGB TRI LEDs
- 4-Button DMX LED Display
- 3 Operational modes: DMX controller, Master/Slave & Sound Active
- 3 DMX Channel modes (1, 4 or 17 Ch.)
- 3-Pin DMX In/Out
- Strobe speed (Controlled via DMX)
- 0-100% dimming (Controlled via DMX)
- Includes exciting sound activate built-in programs
- No Moving Parts
- Runs extremely cool! - NO Duty Cycles! – Run all night!
- Includes dual scissor yoke + safety hook on rear panel
- Power Consumption: 61W maximum
- Compatible with American DJ UC3 Series easy-to-use controllers (sold Separately)
- IEC AC IN/OUT on rear to daisy chain power (up to 6 Pixel Pulse Bar's @ 120V and 10 Pixel Pulse Bar's @ 230V)
- Multi-voltage operation: AC 100-240V 50/60Hz
- Dimensions (LxWxH): 15.5" x 7.25" x 3.5" / 388 x 178.5 x 82mm
- Weight: 8 lbs. / 3.2 kg.

Specifications subject to change without notice

